

Linortek Netbell®- KMB All-In-One Network Multi-Tone Buzzer System

Applications

Provide remote access to control timed alert system for:

- Factories
- Warehouses
- Any other commercial buildings that need a loud timed alert system for breaks, shift changes or general alarms

The Key Features

- Network enabled, access the Netbell from any computer on the network
- All-in-one system, no additional software or designated computer required
- Import/export schedules from existing data in text format
- Flexible and accurate control of when the bells ring (HH:MM:SS,MM/DD/YYYY, SUNDAY- SATURDAY)
- Built-in real time clock sync its time from NTP server every 30 minutes (user changeable)
- Built-in rechargeable battery protected auxiliary real time clock
- Use as either a network device or a standalone device
- Designed, developed and built in the USA with global materials

Self-Contained, Easy-To-Use, Remote Access, Scheduling Buzzer Over the Network, No Additional Software or Designated Computer Required



Linortek Netbell® is an ease-of-use, network enabled, custom developed device for schools, factories, warehouses and other organizations to build a fully automated web-based timed alert system for signaling shift changes, general alarm, and breaks in areas of high ambient noise levels. The system is built on a TCP/IP platform with a built in web server, which allows users to access, control, and schedule the Bells or buzzers accurately and effectively using an Internet connection from anywhere over the network, with no additional software or designated computer required.

The Netbell-KMB includes a built-in high quality multi-tone buzzer ([80 alarm tones](#) with 4 stages, 105dBa@1m, 98dBa @10', volume adjustable) that can be used on any industrial buildings, and a completely wired web-based bell controller installed within a NEMA-rated box. 4 tones can be selected for different events either triggered by schedules, or wiring a push switch to the digital inputs to ring the buzzer manually for emergency.

You can add a 4" LED digital clock to the Netbell-KMB server to sync its time from the Netbell. The digital clock is a plug and play solution, you will only need to plug it into the Netbell clock output; no configuration needed and no additional power source required.

Netbell® Technical Specifications

Netbell All-In-One Extra Loud Buzzer System

General Information			
Model	Netbell-KB	Netbell-KB-M2	Netbell-KMB
Part#	01-910-00022	01-910-00037	01-910-00108
Technical Specification			
Web Server	Built- In (All software located on built-in web server.)		
Event Schedules	Up to 500 Web-Based Event Schedules (Add schedules from web browser)		
Bell Ringing Duration	User Programmable for Each Schedule		
Built-In Bell/Buzzer	1 (4" Vibrating Buzzer,110dBa @ 1m)	1	1 (4" Multi-Tone, 105dBa@1m)
Available Tones	1	1	80 Alarm Tones with 4 Stages
Volume Control	Yes		
Coverage (SQ FT)	25000	25000	25000
Manual Bell Control	Yes		
Push Switch	1 (Included)		
Enclosure	ABS, IP66 /150mm x 150mm x 90mm		
Accessories	3M Power Cable/3M RJ45 Cable/Mounting Brackets		
Power Input	24VAC (included)		
Voltage Sensor	On Board		
Temperature Sensor	On Board		
Rechargeable Battery	On Board (For offline time & settings keeping backup up to 7 days)		
Working Temperature	From 0 to +60 Celsius		
Supported Protocols	HTTP/ SMTP/SNTP		

