

# SmartOnline S3MT-Series 3-Phase 60kVA Input (480V to 208V)/Output (208V to 480V) Isolation Transformers

MODEL NUMBER: **S3MT-60KWR480V**



Enclosure with step-down and step-up transformers offers line isolation and protection to the connected 3-phase UPS and its load.

## Features

### Get Complete Step-Down/Step-Up and Isolation Protection

Tripp Lite's S3MT-60KWR480V includes two transformers in a single cabinet: a 480V (Delta) to 208V (Wye) input isolation step-down transformer and a 208V (Wye) to 480V (Wye) output auto step-up transformer. It isolates the UPS and connected components from line surges and spikes caused by utility power disruptions that can damage equipment or corrupt data. The dual transformers are ideal for 4-wire (3Ph+N+PE) loads in government, manufacturing, healthcare and corporate settings with 480V electrical mains and 480V IT loads.

### Performs with High Efficiency up to 97.5%

Not only is the S3MT-60KWR480V wrap-around transformer very efficient, with up to 97.5 percent efficiency, but it is also very quiet with a noise profile less than 65 dBA. Built-in circuit breakers on both transformers help prevent dangerous power overloads. Eight ball-bearing cooling fans help prevent overheating. An overheat-sensing relay and switch combine with red alarm indicators to provide over-temperature warning and overheating protection.

### Small Footprint for Quick Installation in a Compact Space

The compact footprint enables installation of the S3MT-60KWR480V with minimal space. The rugged stainless steel housing ships ready for immediate tower installation with a compatible 50–60kVA/kW Tripp Lite S3M-Series 3-phase UPS system.

## Highlights

- Dual 60kVA/kW 480V transformers for government, healthcare and corporate settings
- Up to 97.5% efficiency with a quiet acoustic profile less than 65 dBA
- Resettable protection relay/switch and red alarm indicators warn against overheating
- Rugged stainless steel housing with compact footprint comes ready for installation
- Compatible with select 50–60kVA/kW Tripp Lite S3M-Series 208V 3-phase UPS systems

## Applications

Protect equipment in government, healthcare, manufacturing, corporate and other settings that have 480V electrical mains and 480V IT loads

## System Requirements

- 50–60kVA/kW Tripp Lite S3M-Series 208V 3-phase UPS system
- Not compatible with SUT40K or SUT60K

## Package Includes

- S3MT-60KWR480V 3-Phase 60kVA Input/Output Isolation Transformers
- (4) Bottom skirts
- (24) Screws
- Owner's manual

## Specifications

OVERVIEW	
UPC Code	037332253200
Efficiency	96.5% @ 100% load



Nominal Voltage / Frequency	Input transformers (T-in) 480V / Output transformer (T-out) 208V, 3-PH / 60Hz
VA / Watt Capacity	30000
Transformer Type	Dry type, Input step-down isolation transformer and Output step-up Auto Transformer
<b>INPUT</b>	
Nominal Input Voltage(s) Supported	480V 3-PH Delta
UPS Input Connection Type	Hardwire
Input Phase	3-Phase
<b>OUTPUT</b>	
Output Volt Amp Capacity (VA)	60000
Output Capacity (kVA)	60
Output Receptacles	Hardwire
<b>PHYSICAL</b>	
Primary Form Factor	Tower
Cooling Method	8 x BALL BEARING, 120MM (1152 TOTAL CFM)
Form Factors Supported	Tower
Shipping Dimensions (hwd / in.)	70.90 x 27.60 x 37.80
Shipping Weight (kg)	684.92
Unit Dimensions (hwd / in.)	63 x 23.6 x 33.5
Unit Dimensions (hwd / cm)	160 x 60 x 85
Unit Weight (lbs.)	1398
Unit Weight (kg)	634.12
<b>ENVIRONMENTAL</b>	
Heat Dissipation (BTU/Hr) @ Full Load	14334
<b>INPUT TRANSFORMER</b>	
Input Voltage	480V
Input Voltage Range	(-45%, +25%) for 40% load (-20%, +25%) for 100% load
Input Amp(s)	101 A
AC Input Configuration	Delta
AC Input Frequency	50/60
Frequency Range	40/70Hz
Voltage Selection	NONE
Input Inrush Current	920 A



VA Rating	60K
Input Number of Phases	3PH
AC Output Voltage (V)	480 V
AC Output Amps	225 A
Output Number of Phases	3PH + N
AC Output Configuration	WYE
Output Isolation	Yes
Output Breaker Rating	250 A
Connection Type	COPPER BAR
LED Warning Light Functions	The over-temperature warning LED light will turn ON when the output/secondary of the Input transformer reaches 160°C ±5°C and will turn OFF when the corresponding transformer cools down to 125°C ±5°C
Over Temperature Reset	The transformers include an over-temperature protection relay and thermal switch on the secondary sides of the input (T-in) and on the primary side of the output (T-out) transformer to protect the transformer from overheating. Thermal switches on input and output transformers will open the corresponding transformer breaker if either of the transformer reaches 155°C/311°F to 165°C/329°F. Once the transformer cools down to 120°C/248°F to 130°C/266°F, the corresponding warning LED light will turn OFF, and the corresponding transformer breaker maybe closed to restart operation.
Efficiency @ Half Load	97.50%
Efficiency @ Full Load	96.50%
Heat Dissipation (BTU/Hr) @ Full Load	14334
Audible Noise (dBA @ 1m)	65dB max
<b>OUTPUT TRANSFORMER</b>	
Input Voltage	208 V
Input Voltage Range	(-45%,+25%)for 40 % load (-20%,+25%)for 100 % load
Input Amp(s)	173 A
AC Input Configuration	WYE
AC Input Frequency	50/60 HZ
Frequency Range	40-70HZ
Input Inrush Current	2020 A
Input Number of Phases	3PH+N
VA Rating	60K
AC Output Voltage (V)	480 V
AC Output Amps	72 A
Output Number of Phases	3PH+N
AC Output Configuration	WYE
Output Isolation	No
Output Breaker Rating	250 A



Connection Type	COPPER BAR
LED Warning Light Functions	The over-temperature warning LED light will turn ON when the input/primary of the Output transformer reaches 160°C ±5°C and will turn OFF when the corresponding transformer cools down to 125°C ±5°C
Over Temperature Reset	The transformers include an over-temperature protection relay and thermal switch on the secondary sides of the input (T-in) and on the primary side of the output (T-out) transformer to protect the transformer from overheating. Thermal switches on input and output transformers will open the corresponding transformer breaker if either of the transformer reaches 155°C/311°F to 165°C/329°F. Once the transformer cools down to 120°C/248°F to 130°C/266°F, the corresponding warning LED light will turn OFF, and the corresponding transformer breaker maybe closed to restart operation.
Efficiency @ Half Load	97.50%
Efficiency @ Full Load	96.50%
Heat Dissipation (BTU/Hr) @ Full Load	14334
Audible Noise (dBA @ 1m)	65dB max
<b>WARRANTY</b>	
Product Warranty Period (Worldwide)	2-year limited warranty
Product Warranty Period (U.S. & Canada)	2-year limited warranty

© 2021 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice.

Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies:

<https://www.tripplite.com/products/product-certification-agencies>