



**ELECTRONICS, INC.**  
 44 FARRAND STREET  
 BLOOMFIELD, NJ 07003  
 (973) 748-5089  
<http://www.nteinc.com>

## NTE3021 and NTE3022 Light Emitting Diode (LED) 5mm (T-1 3/4) Type Package

**Description:**

The NTE3021 and NTE3022 are discrete LED indicators in a 5mm (T-1 3/4) type package. The NTE3021 yellow source color device is made with GaAlInP/GaAsP and a yellow diffused lens while the NTE3022 red source color device is made with GaP/GaP on a red diffused lens.

**Features:**

- Low Power Consumption
- IC Compatible
- Long Life Solid State Reliability
- Diffused Lens

**Absolute Maximum Ratings:** ( $T_A = +25^\circ\text{C}$  unless otherwise specified)

Reverse Voltage, $V_R$ .....	5V
Power Dissipation, $P_D$	
NTE3021 .....	85mW
NTE3022 .....	75mW
Continuous Forward Current, $I_F$ .....	30mA
Derate linear from $+25^\circ\text{C}$ .....	$0.4\text{mA}/^\circ\text{C}$
Peak Forward Current (1/10 Duty Cycle, 0.1ms Pulse Width), $I_{F(\text{Peak})}$ .....	100mA
Operating Temperature Range, $T_A$	
NTE3021 .....	$-40^\circ$ to $+85^\circ\text{C}$
NTE3022 .....	$-25^\circ$ to $+85^\circ\text{C}$
Storage Temperature Range, $T_{\text{stg}}$ .....	$-40^\circ$ to $+85^\circ\text{C}$
Lead Temperature (During Soldering, .063 in. (1.6mm) from Body for 3sec), $T_L$ .....	$+260^\circ\text{C}$

**Electrical/Optical Characteristics:** ( $T_A = +25^\circ\text{C}$  unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Forward Voltage	$V_F$	$I_F = 20\text{mA}$	1.8	2.0	2.2	V
Reverse Current	$I_R$	$V_R = 5\text{V}$	-	-	10	$\mu\text{A}$
Dominant Wavelength	$\lambda_D$	$I_F = 20\text{mA}$				
NTE3021			584	586	588	nm
NTE3022			635	-	640	nm

Rev. 11-15



**Electrical/Optical Characteristics (Cont'd):** ( $T_A = +25^\circ\text{C}$  unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Spectral Line Half Width NTE3021 <b>ONLY</b>	$\Delta\lambda$	$I_F = 20\text{mA}$	-	30	-	nm
Half Intensity Angle NTE3021 NTE3022	$2\theta^{1/2}$	$I_F = 20\text{mA}$	- 30	40 40	- 50	deg deg
Luminous Intensity NTE3021	$I_V$	$I_F = 20\text{mA}$	-	50	-	mcd
		$I_F = 10\text{mA}$	-	25	-	mcd
NTE3022		$I_F = 20\text{mA}$	40	60	80	mcd

