

# Spectrum Compact 24-40/43 GHz v.2

JOSSAP74 / JOSSAP54 datasheet



## Measurements

- Channel Power (measures the total power in a specified bandwidth)
- Adjacent channel power
- Signal bandwidth
- Center frequency
- Interference detection
- Mask

## Setup Parameters

- Frequency: Center/Start/Stop
- Trace mode: Normal, Max hold, Cumulative, # of Averages, Fill, MinMax Hold
- Span: Full Span, Min Span, Selected Span

## Save

- Proprietary format
- Saves actual data

## Sweep Functions

- Sweep: Continuous, Manual Trigger

## Trace Functions

- Trace operations: Normal, Max hold, # of Averages, Cumulative, MinMax Hold

## Marker Functions

- Marker: Peak search, set marker to center

## Settings

- RBW, VBW

SAF Spectrum Compact 24-40/43GHz v.2 datasheet

Product features may vary between different models and configurations. They are subject to change without prior notice.



# Spectrum Compact 24-40/43 GHz v.2

J0SSAP74 / J0SSAP54 datasheet



<b>Display</b>	
Type	Touchscreen
Resolution	480 x 3 (RGB) x 272
Size	4.3 inch
Color arrangement	RGB-stripe
<b>Mass memory</b>	8 GB
<b>Input voltage</b>	5V DC 3A
<b>Interface</b>	USB Type-C
<b>Battery life</b>	up to 3h
<b>Operating temperature</b>	-15°C to +55°C / 5°F to 131°F
<b>Dimensions</b>	135 x 83 x 34 mm / 5.31 x 3.27 x 1.34 inch
<b>Weight</b>	0.57 kg / 20.11 oz

For more detailed information about SAF products visit [www.saftehnika.com](http://www.saftehnika.com) or contact your SAF representative [info@saftehnika.com](mailto:info@saftehnika.com). Product features may vary between different models and configurations. They are subject to change without prior notice.

SAF Tehnika © 2019

*SAF Spectrum Compact 24-40/43GHz v.2 datasheet*

*Product features may vary between different models and configurations. They are subject to change without prior notice.*