

	1	2	3	4	5	6	7																																																																																																	
A					<b>NOTES:</b> <b>1.Material:</b> 1.1 Housing: LCP+30%GF UL94V-0, Color Blue 1.2 Cover: LCP +30%GF UL94V-0, Color Blue 1.3 Shell: SPCC 1.4 Contact :Phosphor Bronze <b>2. FINISH:</b> 2.1 Contact Area: Selective 15u"Au Solder Area:80u"Tin Plated Under: 30u"Ni Plated <b>3.MECHANICAL:</b> 3.1 Mating Force:3.57kgf Max. 3.2 Unmating Force:1.02kgf Min ② 3.3 Durability:5000 cycles Min <b>4.ELECTRICAL:</b> 4.1 Current Rating:1.0A for Pin1~4, 0.25A for other PIN 4.2 Dielectric Strength:500V AC FOR 1 MINUTE 4.3 Contact Resistance: 20mΩ Max for Pin1ToPin4,50mΩ for other PIN 4.4 Insulation Resistance:100 MΩ Min <b>5.Operating temperature: -40°C TO +85°C</b> <b>6.PACKIING:</b> A-USB3 A-LP-SMT1 Tray ⑤ A-USB3 A-LP-SMT1-R Tape & Reel, Packing info as below Qty per reel: 500PCS Qty per carton: 3500PCS Tape&Reel size: Ø35cm Carton size: 35*35*29.6cm				A																																																																																															
B									B																																																																																															
C									C																																																																																															
D									D																																																																																															
E									E																																																																																															
F	SECTION A-A RECOMMENDED P.C.B LAYOUT (TOLERANCE:±0.05)								F																																																																																															
G	<b>RoHS compliant</b>				<table border="1"> <thead> <tr> <th>Scale</th> <th>Free</th> <th>⑤</th> <th>Add the Part A-USB3 A-LP-SMT1-R and its packing info.</th> <th>05.06.2019</th> <th>Xavier</th> <th></th> <th>Date</th> <th>Name</th> <th>Customer-No.</th> </tr> </thead> <tbody> <tr> <td colspan="2"><b>TOLERANCE</b></td> <td>④</td> <td>Change the P/N to A-USB3 A-LP-SMT1</td> <td>23.12.2016</td> <td>Winnie</td> <td>Drawn</td> <td>07.06.2013</td> <td>Winnie</td> <td rowspan="3">ASSMANN WSW-No. ⑤④ A-USB3 A-LP-SMT1-x</td> </tr> <tr> <td>.X</td> <td>±0.30</td> <td>③</td> <td>Add the dimension of hole in PCB</td> <td>25.02.2014</td> <td>Winnie</td> <td>Approved</td> <td>05.06.2019</td> <td>Winnie</td> </tr> <tr> <td>.XX</td> <td>±0.20</td> <td>②</td> <td>Update the dimension</td> <td>31.10.2013</td> <td>Winnie</td> <td></td> <td></td> <td></td> </tr> <tr> <td>.XXX</td> <td>±0.10</td> <td>①</td> <td>Re-drawn</td> <td>17.10.2013</td> <td>Winnie</td> <td></td> <td></td> <td></td> <td>Drawing-No.</td> </tr> <tr> <td>DIM</td> <td>TOL</td> <td>①</td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td rowspan="2">ASS 5765 CO</td> </tr> <tr> <td>X.°</td> <td>±5°</td> <td>①</td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td>rev05</td> </tr> <tr> <td>Angle</td> <td>TOL</td> <td>①</td> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td>Replace</td> </tr> <tr> <td>UNIT</td> <td>mm</td> <td>Id.</td> <td>Modification</td> <td>Date</td> <td>Name</td> <td colspan="3" rowspan="2"> </td> <td>SHEET</td> </tr> <tr> <td></td> <td></td> <td></td> <td></td> <td></td> <td></td> <td>1/1</td> </tr> </tbody> </table>				Scale	Free	⑤	Add the Part A-USB3 A-LP-SMT1-R and its packing info.	05.06.2019	Xavier		Date	Name	Customer-No.	<b>TOLERANCE</b>		④	Change the P/N to A-USB3 A-LP-SMT1	23.12.2016	Winnie	Drawn	07.06.2013	Winnie	ASSMANN WSW-No. ⑤④ A-USB3 A-LP-SMT1-x	.X	±0.30	③	Add the dimension of hole in PCB	25.02.2014	Winnie	Approved	05.06.2019	Winnie	.XX	±0.20	②	Update the dimension	31.10.2013	Winnie				.XXX	±0.10	①	Re-drawn	17.10.2013	Winnie				Drawing-No.	DIM	TOL	①							ASS 5765 CO	X.°	±5°	①							rev05	Angle	TOL	①							Replace	UNIT	mm	Id.	Modification	Date	Name				SHEET							1/1	G
Scale	Free	⑤	Add the Part A-USB3 A-LP-SMT1-R and its packing info.	05.06.2019	Xavier		Date	Name	Customer-No.																																																																																															
<b>TOLERANCE</b>		④	Change the P/N to A-USB3 A-LP-SMT1	23.12.2016	Winnie	Drawn	07.06.2013	Winnie	ASSMANN WSW-No. ⑤④ A-USB3 A-LP-SMT1-x																																																																																															
.X	±0.30	③	Add the dimension of hole in PCB	25.02.2014	Winnie	Approved	05.06.2019	Winnie																																																																																																
.XX	±0.20	②	Update the dimension	31.10.2013	Winnie																																																																																																			
.XXX	±0.10	①	Re-drawn	17.10.2013	Winnie				Drawing-No.																																																																																															
DIM	TOL	①							ASS 5765 CO																																																																																															
X.°	±5°	①								rev05																																																																																														
Angle	TOL	①							Replace																																																																																															
UNIT	mm	Id.	Modification	Date	Name				SHEET																																																																																															
									1/1																																																																																															
H									H																																																																																															
	1	2	3	4	5	6	7																																																																																																	