RMTK80BD

Harmony Analog, Converter for thermocouples, temperature transmitter, 0...600 °C/32...112 °F



Main	
Range of Product	Harmony Analog
Product or Component Type	Converter for thermocouples
Analogue input type	Thermocouple 0600 °C/321112 °F thermocouple K IEC 60584
Analogue output type	Current 020 mA <= 500 Ohm Current 420 mA <= 500 Ohm Voltage 010 V >= 100 kOhm

Complementary

Protection Type	Overvoltage protection on output (+/- 30 V) Reverse polarity protection on output Short-circuit protection on output
Abnormal analogue output voltage	-1511 V no input or input wire broken 1115 V no input or input wire broken
Abnormal analogue output current	-300 mA no input or input wire broken
[Us] rated supply voltage	24 V DC +/- 20 %, non isolated
Current consumption	<= 40 mA voltage output <= 60 mA current output
Local signalling	For power ON LED (green)
Measurement error	+/- 10 % of full scale 20 °C electromagnetic interference of 10 V/m) +/- 1 % of full scale 20 °C
Repeat accuracy	+/- 0.25 % full scale 20 °C +/- 0.8 % full scale 60 °C
Temperature coefficient	200 ppm/°C
Cold junction compensation	Built-in between 0 and 60 °C
Clamping connection capacity	1 x 2.5 mm² 2 x 1.5 mm²
Tightening torque	5.319.74 lbf.in (0.61.1 N.m)
Marking	CE
Surge withstand	0.5 kV 1.2/50 μs IEC 61000-4-5
[Ui] rated insulation voltage	2 kV
Fixing mode	By screws mounting plate) Clip-on 35 mm symmetrical DIN rail)
Safety reliability data	MTTFd = 49.2 years B10d = 45447
Net Weight	0.26 lb(US) (0.12 kg)

Environment

Standards	IEC 60584-1 IEC 60947-1
Product Certifications	CSA UL GL
IP degree of protection	IP20 terminal block) IP50 housing)
Fire resistance	1562 °F (850 °C) IEC 60695-2-1 1562 °F (850 °C) UL
Shock resistance	50 gn 11 ms IEC 60068-2-27
Vibration resistance	5 gn 10100 Hz)IEC 60068-2-6
Resistance to electrostatic discharge	6 KV in contact)IEC 61000-4-2 level 3 8 kV in air)IEC 61000-4-2 level 3
Resistance to fast transients	1 KV IEC 61000-4-4 on input-output) 2 kV IEC 61000-4-4 on power supply)
Disturbance radiated/conducted	CISPR 11 CISPR 22 group 1 - class B
Ambient Air Temperature for Storage	-40185 °F (-4085 °C)
Ambient Air Temperature for Operation	32122 °F (050 °C) mounting side by side 32140 °F (060 °C) 2 cm spacing
Pollution degree	2 IEC 60664-1

Ordering and shipping details

22375 - INTERFACE MODULE(ABA,R,S)
CP2
3389110109054
1
3.56 oz (101 g)
No
ID

Packing Units

Unit Type of Package 1	PCE
Package 1 Height	1.06 in (2.7 cm)
Package 1 width	3.23 in (8.2 cm)
Package 1 Length	3.35 in (8.5 cm)
Unit Type of Package 2	S02
Number of Units in Package 2	47
Package 2 Weight	11.56 lb(US) (5.245 kg)
Package 2 Height	5.91 in (15 cm)
Package 2 width	11.81 in (30 cm)
Package 2 Length	15.75 in (40 cm)

Offer Sustainability

Sustainable offer status	Green Premium product
California proposition 65	WARNING: This product can expose you to chemicals including: Nickel compounds, which is known to the State of California to cause cancer, and Di-isodecyl phthalate (DIDP), which is known to the State of California to cause birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov
REACh Regulation	☑ REACh Declaration
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)
Mercury free	Yes
RoHS exemption information	₫Yes
China RoHS Regulation	☑ China RoHS Declaration


Environmental Disclosure	Product Environmental Profile
Circularity Profile	☑ End Of Life Information
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins.
Contractual warranty	
Warranty	18 months

Product data sheet Dimensions Drawings

RMTK80BD

Analog Interface (Converter)

Dimensions




(1) Terminal block AB1TP435U or AB1RRNTP435U2

Product data sheet Mounting and Clearance


RMTK80BD

Mounting

Mounting on Rails AM1 *****



Panel Mounting




Product data sheet Connections and Schema

RMTK80BD

Analog Interfaces

Wiring Diagram



The input, output and power supply lines must be kept away from the power cables to avoid effects due to induced interference. The input and output cables must be shielded as indicated in the diagram and must be kept away from each other.