

Product Overview

AR023Z: CMOS Image Sensor, 2 MP, 1/2.7"

For complete documentation, see the data sheet.



The AR023Z is a 1/2.7-inch CMOS digital image sensor with an active-pixel array of 1928Hx1088V. It captures images in either linear or high dynamic range modes, with rolling-shutter readout. It includes sophisticated camera functions such as in-pixel binning, windowing and both video and single frame modes. It is designed for both low light and high dynamic range scene performance. It is programmable through a simple two wire serial interface. The AR023Z produces extraordinarily clear, sharp digital pictures, and its ability to capture both continuous video and single frames makes it the perfect choice for a wide range of applications, including home monitoring and smart appliances.

Features

- High Dynamic Range

Applications

- IoT

Part Electrical Specifications

Product	Compliance	Status	Type	Megapixels	Frame Rate (fps)	Optical Format	Shutter Type	Pixel Size (µm)	Output Interface	Color	Package Type
AR023ZMCSC00SUEA 0-DRBR	Pb-free Halide free	Active	CMOS	2.1	60	1/2.7 inch	Electronic Rolling	3.0 x 3.0	Multi	Bayer Color	IBGA-80

For more information please contact your local sales support at www.onsemi.com.

Created on: 9/8/2019